Honeywell

SAFETY SUITE DEVICE CONFIGURATOR (SSDC)

BW ULTRA DEAKTIVACE MODULU BLUETOOTH





1. Přihlašte se do počítačového programu Honeywell SSDC.

> 2. Připojte detektor BW Ultra pomocí IR-Link adaptéru s kabelem.

Na obrázku vpravo vidíme displej detektoru BW Ultra se zapnutým modulem Bluetooth. To známená, že je možné se k detektoru připojit mobilním zařízením pomocí aplikace Honeywell Device Configurator.

Pres and

3. V počítačovém programu SSDC po obnovení připojených zařízení (filtr "connected" a refresh) klikneme na sériové číslo detektoru u kterého chceme změnit nastavení.

13:47	* 881
20.9 % 0 堤	
O Voc	i f
, ů E	
Honeywell BW Ultra	an j
	1 the

Device List View	Templates	Custo	om F	ields									
10 devices shown	i i i i pracoo	ouou		10100		O Update Firmware	Printable Config	占 Download Data 🛛 🕫 Set Para	ameters 🔹 Event Logs	Bump/Cal Resu	its 📋 Datalogs 🛃 Export Datalogs	Columns	O Refres
Filter by	Clear All	Conr	nection	Connected ×							Search IntelliDoX IDe	Search A	toPAE2 II
CONNECTION	Clear								<u> </u>		Search Intembox IPs	General	atomacz n
Connected	00		6 ⁰ S	SERIAL NUMBER	FIRMWARE VERSION	DEVICE TYPE	MODEL NUMBER	LAST SUCCESSFUL CALIBRATIC	A LAST DOWNLOAD DATE	LC DEVICE STATUS	DATUM PRODEJE POZNAMKY	UZIVATEL	SE
Not Connected	8		e ⁰ (5220ULT01243600143	V1.026	BW Ultra	BW Ultra	11/03/2025	11/03/2025	Active			
DEVICE STATUS	Clear		60	522000X01232900080	V12.600	IntelliDoX	BW Icon / BW Flex		07/03/2025	Active			
SERIAL NUMBER	Clear		60	5220D0X01191900002	V12.401	IntelliDoX	BW Solo	-	05/03/2025	Active			
LOCATION	Clear		e ⁹	5220D0X01174200016	V12.401	IntelliDoX	GasAlertMicroClip		28/02/2025	Active			
DEVICES	Clear		00	5220D0X01221300084	V12.401	IntelliDoX	GasAlertMicroClip	-	28/02/2025	Active			
Instruments			e ⁰	5220D0X01222700119	V12.401	IntelliDoX	BW Ultra	-	26/02/2025	Active			
BW Ultra	(1)		60	5220D0X01173000028	V12.401	IntelliDoX	BW Clip	-	06/12/2024	Active			
Docks			6 ⁹	<u>Z322-000608</u>	-	MicroDock II	MicroDock II	105	18/07/2024	Active			
IntellidoxForMicroClip	(3)		6 ⁰	5220D0X01240200048	V12.401	IntelliDoX	GasAlertMicroClip	122	22 C	Active			
IntellidoxForBWicon	(2)												
IntelliDoXForBWSolo	(1)												
IntelliDoXForBWUltra	(1)												
IntellidoxForBWClip	(1)												
MicroDock II	(1)												
ASSIGNED WORKER	Clear												
LAST DOWNLOAD DATE/LOG	- Clear												
LAST SUCCESSFUL BUMP	Clear												
LAST SUCCESSFUL CALIBRAT.	- Clear												

S.r.o.

uite Device Configurator			V	Ę	8
SACK TO DEVICE LIST 5220ULT01243600143 BW Ultra					
INSTRUMENTS OPERATION					
Stealth Mode	Hole Watch Mode	Flip Display			
Disable Power Off Button	BLE PAIRING PIN 100000	Lockout on self test error			
2 02 Sensor Installed	2nd Slot Sensor Installed	3rd Slot Sensor Installed			
LEL Sensor Installed	Sth Slot Sensor Installed	Vormal Display			
BLE enabled	BLE MODE APP Mode				
INTELLIFILASH MODE	Confidence Beep	LANGUAGE English			
INTELLIFLASH INTERVAL sec	CONFIDENCE BEEP INTELLIF	CLEAR PEAKS TWAYSTELL + Peaks			
- LOVE	1-120 sec.				
		RESTORE DEFAULTS UNDO CHANGES	S	AVE	SAVE

4. Pro vypnutí modulu Bluetooth odškrtneme políčko s názvem "BLE enabled" v záložce "Settings".

5. Úpravu nastavení musíme uložit do detektoru pomocí tlačítka "SAVE" v pravém spodním rohu.

😌 Safety S	Suite Device Configurator			
Saf	ety Suite Device Configurator			0 8 🗐 🖾
G	CRACK TO DEVICE LIST 5220ULT01243600143 BW Ultra			
~	INSTRUMENTS OPERATION			
88	Stealth Mode	Hole Watch Mode	Flip Display	
	Disable Power Off Button	BLE PAIRING PIN 100000	Lockout on self test error	1
	02 Sensor Installed	2nd Slot Sensor Installed	3rd Slot Sensor Installed	
	LEL Sensor Installed	5th Slot Sensor Installed	Vormal Display	
	BLE enabled	APP Mode.		
	INSTRUMENT USER PREFERENCES			
	INTELLIFLASH MODE IntelliFlash Enabled	Confidence Beep	LANGUAGE	
	INTELLIFLASH INTERVAL 1 - 120 sec	CONFIDENCE BEEP INTELLIF	CLEAR PEAKS TWA/STEL + Peaks	
	STARTUP MESSAGE			
			RESTORE DEFAULTS UNDO CHANGE	SAVE SAVE AS FILE
				1 C
		S.ľ.O.		

6. Pokud vše proběhlo správně tak na horní liště displeje detektoru zmizí ikonka Bluetooth.

Nyní se k detektoru BW Ultra nelze bezdrátově připojit!

MLEL

VOC

ř

.....

~ Ô

Honeywell BW Ultra

S.r.o.

Pro více informaci navštivte naše webové stránky www.detektory-plynu.cz

1



Zajímavá videa a videonávody naleznete na našem YouTube kanále www.youtube.com/@detektoryplynu



